

# ((( CareTech®

Call for care

No power adapter required

Real-time clock

Built-in event log



## Gina Carephone

CareTech has been developing carephones for over 25 years and we feel confident in saying that we understand care telephony well. Very well in fact. We develop our products and solutions in collaboration with our customers. This is one of the reasons why CareTech carephones are so easy to install and use.

Gina is a practical, well-designed, battery-operated carephone that is ideal for use in the individual's own home. The real-time clock adds the flexibility of time-controlled features and the built-in event log enables quality of care to be monitored. A wide choice of accessories, including alarm triggers, bedside alarms and door alarms can be connected to Gina to create the ideal solution for any situation.



# Gina Carephone

With just a single press on the alarm button the Gina carephone alerts care staff or the alarm monitoring centre. The person who takes the alarm call can then talk directly to the person who raised the alarm and take suitable action. Wireless accessories, such as CareTech's Erik and Elliot radio triggers, smoke alarms, bedside alarms, door alarms, etc., can easily be linked to the carephone. The risk of lightning damage is minimized by connecting solely through the telephone network and by the effective lightning protection built into the Gina carephone.

- Built-in real-time clock with year, date, day and time display to the second, suitable for timed control of doors, bed and passive alarm.
- Facility for wireless remote control.
- Supports care monitoring, including i-care.
- Buttons for alarm, presence and reset.
- Alarms can be forwarded to manned/unmanned alarm centres, landline telephones and mobile telephones.
- Callback function.
- Ability for home care staff to send assault alarm using a special radio trigger, without previous programming.
- Ability to answer incoming telephone calls using the portable radio trigger.
- Log alarm, test alarm, passive alarm, range check, etc.
- Line fault detection.
- Ability to control volume from a landline telephone, mobile telephone or alarm centre.
- Programming can be carried out from a landline telephone, mobile telephone, programming unit, CareTech remote programming or from a PC with appropriate software.
- Able to interrupt existing telephone calls if necessary.
- Environmentally friendly batteries.
- Supports various dementia solutions.
- Can easily be upgraded and expanded with new services and features.
- Complies with all relevant EU directives and standards.
- Supplied complete with Erik radio alarm button.

## Technical data

Power supply	Telephone network and battery
Battery, central unit	4 x LR6 Alkaline (1.5 V 2700 mAh)
Battery backup	2-3 years
Battery alarm	Triggered automatically at central unit if battery voltage is low
Speech communication	Duplex and simplex
Radio	Long-term station keeping, 868.35 MHz
No. of radio transmitters	Up to 9 radio transmitters
Dialling method	DTMF (touch tone) or pulse
Alarm receiver	Up to 6 alarm receivers can be programmed. Max. 15 digits in telephone number or 12 digits in alarm code
Protocol	Smart Call, Antenna, Attendo TT90/CPC, Vitalcall/Tunstall and landline telephone
Dimensions	215 x 125 x 45 mm
For more information	See Technical Manual
Article number	1-8400-110

## Approval

CE-marked. Complies with R&TTE 1999/5/EC requirements for the following standards:

EMC	EN 50130-4:1995, A1:1998, A2:2003, EN 301 489-3 V1.4.1 (2002-08)
	EN 50134-3
SRD Radio	EN 300 220-3 V1.1.1 (2000-09)

Low Voltage Directive EN 60 950-1:2002, A11:2004, C1:2004

Manufactured in accordance with the new RoHS directive, 2002/95/EC



(Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment)

**CareTech**®  
Call for care

Caretech System PTY LTD  
Box 83 Clontarf Beach  
Tel: (07) 32842700  
Fax: (07) 32842502  
sales@caretech.com.au  
www.caretech.com.au